




PCFM Agile FM Stereo Audio Modulator

- 35dBmV minimum adjustable output for optimum carrier to noise performance
- Frequency Range 88~108MHz (FM Band)
- Agile push-button tuning and digital display for easy frequency selection
- Non-volatile memory for last channel recall in the event of power failure
- Switch-selectable between stereo and monaural operation
- Signal to noise ratio >60dB provides superior sound quality
- Front panel test point for easy RF level system monitoring
- Auxiliary AC outlet for convenience
- UL Approved



Front View



Rear View

Specifications

Output Frequency Range	88~108MHz	Power Output	Yes
Tuning	Agile	Receptacle	
RF Output Level (min)	35dBmV	Dimensions	19"(L) x 3"(D) x 1.75"(H)
Spurious Output	>65dB	Weight	3.6 lbs.
Audio Input Type	Monaural/Stereo		
Audio Frequency			
Response	50~15,000Hz		
Audio Input Connection	600 F-Female Unbalanced		
RF Output Connection	75 F-Female		
Voltage Input	115VAC		

Ordering Information

PCFM Agile FM Stereo Audio Modulator