



Band	VHF/CABLE Channels			
	TV Channel		Visual Carrier Mhz	
	Alpha-Num.	Num. Equiv.	Standard	HRC
SUB	T-7	..	7	..
	T-8	..	13	..
	T-9	..	19	..
	T-10	..	25	..
	T-11	..	31	..
	T-12	..	37	..
	T-13	..	43	..
VHF LOW	2	2	55.25	54
	3	3	61.25	60
	4	4	67.25	66
	A-8	1	..	72
	5*	5	77.25	78
	6*	6	83.25	84
Mid	A-5	95	91.25	90
	A-4	96	97.25	96
	A-3	97	103.25	102
	A-2	98	109.25	108
	A-1	99	115.25	114
	A	14	121.25	120
	B	15	127.25	126
	C	16	133.25	132
	D	17	139.25	138
	E	18	145.25	144
	F	19	151.25	150
	G	20	157.25	156
	H	21	163.25	162
	I	22	169.25	168
VHF High	7	7	175.25	174
	8	8	181.25	180
	9	9	187.25	186
	10	10	193.25	192
	11	11	199.25	198
	12	12	205.25	204
	13	13	211.25	210
Super	J	23	217.25	216
	K	24	223.25	222
	L	25	229.25	228
	M	26	235.25	234
	N	27	241.25	240
	O	28	247.25	246
	P	29	253.25	252
	Q	30	259.25	258
	R	31	265.25	264
	S	32	271.25	270
	T	33	277.25	276
U	34	283.25	282	

V	35	289.25	288
W	36	295.25	294

*ch 5&6 (HRC only), also referred to as A-7 & A-6 respectively



Band	Cable Channels			
	TV Channel		Visual Carrier Mhz	
	Alpha-Num.	Num. Equiv.	Standard	HRC
Hyper	AA	37	301.25	300
	BB	38	307.25	306
	CC	39	313.25	312
	DD	40	319.25	318
	EE	41	325.25	324
	FF	42	331.25	330
	GG	43	337.25	336
	HH	44	343.25	342
	II	45	349.25	348
	JJ	46	355.25	354
	KK	47	361.25	360
	LL	48	367.25	366
	MM	49	373.25	372
	NN	50	379.25	378
	OO	51	385.25	384
	PP	52	391.25	390
	QQ	53	397.25	396
	RR	54	403.25	402
	SS	55	409.25	408
	TT	56	415.25	414
	UU	57	421.25	420
	VV	58	427.15	426
WW	59	433.25	432	
XX	60	439.25	438	
YY	61	445.25	444	
ZZ	62	451.25	450	
Ultra	AAA	63	457.25	456
	BBB	64	463.25	462
	CCC	65	469.25	468
	DDD	66	475.25	474
	EEE	67	481.25	480
	FFF	68	487.52	486
	GGG	69	493.25	492
	HHH	70	499.25	498
	III	71	505.25	504
	JJJ	72	511.25	510
	KKK	73	517.25	516
	LLL	74	523.25	522
	MMM	75	529.25	528
	NNN	76	535.25	534

	OOO	77	541.25	540
	PPP	78	547.25	546
	QQQ	79	553.25	552
	RRR	80	559.25	558
	SSS	81	565.25	565
	TTT	82	571.25	570
	UUU	83	577.25	576
	VVV	84	583.25	582
	WWW	85	589.25	588
	XXX	86	595.25	594
	YYY	87	601.25	600
	ZZZ	88	607.25	606
	UHF Channels			
	Non-Cable Broadcast Chs.			
Band	Ch.	Visual Carrier	Ch.	Visual Carrier
UHF	14	471.25	42	639.25
	15	477.25	43	645.25
	16	483.25	44	651.25
	17	495.25	45	657.25
	18	501.25	46	663.25
	19	507.25	47	669.25
	20	513.25	48	675.25
	21	513.25	49	681.25
	22	519.25	50	687.25
	23	525.25	51	693.25
	24	531.25	52	699.25
	25	537.25	53	705.25
	26	543.25	54	711.25
	27	549.25	55	717.25
	28	555.25	56	723.25
	29	561.25	57	729.25
	30	567.25	58	735.25
	31	573.25	59	741.25
	32	579.25	60	747.25
	33	585.25	61	753.25
	34	591.25	62	759.25
35	597.25	63	765.25	
36	603.25	64	771.25	
37	609.25	65	777.25	
38	615.25	66	783.25	
39	621.25	67	789.25	
40	627.25	68	795.25	
41	633.25	69	801.25	
Note: Although the FM band is not listed, it is located between 88-108Mhz, in the same space as the A-2 to A-5 cable channels.				



